

REVAMP1680

16-channel bridgeable digital power amplifier, 16 x 80W, 4oh



REVAMP1680 is a professional 16-channel digital power amplifier with 16 x 100 watts output power @ 4 ohms, but the unit is also bridgeable to 8 x 200 watts @ 8 ohms. This 3 rack units high amplifier with very high channel separation also has a dual analog power supply with toroidal power transformers. The standby power consumption is very low, less than 0.5 watts!

Another smart feature of the REVAMP1680 is the switching mode standby power supply with multiple auto power on/off options. You can power on or power off the unit via a trigger input, audio sense... The trigger input is ideal when you want to switch on the power amplifier automatically using an external AC or DC trigger signal coming from your audio system. The amplifier will be switched on as long as the trigger voltage is present.

Alternatively, you can set the power on mode switch to the audio trig position: the amp will automatically switch on when a sufficiently strong audio signal is present at the input and automatically switch off after a few minutes of silence.

This amplifier is equipped with 2 stereo bus inputs with pass through. These bus inputs are ideal when you want to hear the same audio signal in different output zones with the advantages you need less audio cables and the installation can be done very fast.

With its very low standby consumption and the fact the amplifier can easily be integrated in any audio project, the REVAMP1680 will soon become your favourite multi channel power amplifier.

TECHNICAL SPECIFICATIONS

dynamic output power 4 ohms in watts	16 x 100	RMS output power 4 ohms in watts	16 x 80
dynamic output power 8 ohms in watts	16 x 60	RMS output power 8 ohms in watts	16 x 40
dynamic output power bridged 8 ohms in watts	8 x 200	output power RMS bridged 8 ohms in watts	8 x 160
minimum impedance load per channel in ohms	4	minimum impedance load bridged per channel in ohms	8
power consumption (max) in watts	1350	19" (483 mm wide) rack mounting	yes
height- rack units (1U=44 mm) in U	3	depth (build in) in mm	405
depth (incl front) in mm	421	power supply	115 - 230 VAC
power supply technology	toroidal transformers	output channels	16
line input unbalanced	20	channel separation	> 68 dB @ 1 kHz
power amp topology	class-D	frequency response (in Hz)	20 - 30 k
cooling system	convection	applicable low impedance	yes
Net weight product (kg)	21.70		

[MORE PICTURES](#)

